
# **TURBO LOW NOISE HAND DRYER** 250/251/254

**Touchless** Powerful low-noise 5-year warranty





### **Technical data**

Туре	TURBO LOW NOISE HAND DRYER Prod. No.: 250, 251, 254
	Warm-air hand dryer with IR- sensor
Dimensions	H:11.29 x W: 8.07 x D: 7.08"
Material	250: Steel/enamel, white 251: Stainless steel, brushed 254: Stainless steel, black
Drying cycle	10-15 sec.
Connection	110-120 V, 50/60 Hz Class I
Total wattage	700-1400 W
Heating element	350-700 W (adjustable)
Motor	350-700 W (adjustable)
Noise level	62.8-68.2 dbA @ 39"
Max. air volume	2.35 yd³ /min
Max. air capacity	213'-311' /sec. (adjustable)
Max. air outlet temperature	131 F
Net weight	12.13 lb
IP rating	IP31
Tender text	Touch-free low noise hand dryer with cabinet in steel/enamel, brushed/painted stainless steel. Infrared sensor and electronic timer, drying cycle: 10-15 sec. IP31, 110 V, 50/60 Hz, 700-1400 W, Class I (earthed). 62.8-68.2 dBA. Net weight 12.13 lb. H:11.29 x W: 8.07 x D: 7.08"

#### **Application**

TURBO Low Noise is a hand dryer that manages to combine power with a lower sound level without compromising on short drying time. Featuring long service life and low energy consumption, the machine is an eco-friendly choice for all high-traffic public and commercial areas.

### References


Offices and administration, shopping malls, restaurants, hotels, airports, sports facilities and public swimming pools, schools, public institutions, and cultural centres.

#### Standard colours

Prod. No.: 250, White enamelled steel. Prod. No.: 251, Brushed stainless steel. Prod. No.: 254, Matt black stainless steel.

#### Motor type

Commutator motor with carbon brushes.12,000-18,000 revolutions/min.



#### Activation

Touch-free. Infrared sensor and electronic timer. Activation distance adjustable between 5.9-7.5". Automatic stop after 60 seconds of continuous use.

## **Protection**

Automatic thermal cut-out in both motor and heating element.

# Installation

Machine intended for wall-mounting and fixed installation via circuit-breaker. Installation must be carried out by a qualified electrician.











